

Modelo de VFD HNC HV10	Corriente de entrada (A)	Corriente de salida (A)	Potencia del motor (KW) (HP)	
<b>G1 input voltage range: Single-phase AC120V±15%, 50 / 60 Hz</b>				
HV10-R40G1-1	9	2.3	0.4	0.5
HV10-R75G1-1	15	4.0	0.75	1
HV10-1R5G1-1	24	7.0	1.5	2
HV10-2R2G1-1	31	9.6	2.2	3
<b>G1 input voltage range: Single-phase AC220V±15%, 50 / 60 Hz</b>				
HV10-R40G1-2	5.4	2.3	0.4	0.5
HV10-R75G1-2	8.2	4.0	0.75	1
HV10-1R5G1-2	14	7.0	1.5	2
HV10-2R2G1-2	23	9.6	2.2	3
<b>G2 input voltage range: Three-phase AC220V±15%, 50 / 60 Hz</b>				
HV10-R40G2	3.4	2.1	0.4	0.5
HV10-R75G2	5.0	3.8	0.75	1.0
HV10-1R5G2	5.8	5.1	1.5	2
HV10-2R2G2	10.5	9	2.2	3
HV10-004G2	14.6	13	4	5
<b>G3 input voltage range: Three-phase AC 380~440 (-15%~+10%), 50 / 60 Hz</b>				
HV10-R75G3	3.4	2.1	0.75	1
HV10-1R5G3	5.0	3.8	1.5	2
HV10-2R2G3	5.8	5.1	2.2	3
HV10-004G3	10.5	9	4.0	5
HV10-5R5G3	14.6	13	5.5	7.5
<b>G4 input voltage range: Three-phase AC 440~480 (-15%~+10%), 50 / 60 Hz</b>				
HV10-R75G4	4.1	2.5	0.75	1.0
HV10-1R5G4	4.9	3.7	1.5	2.0
HV10-2R2G4	5.7	5.0	2.2	2
HV10-004G4	11	8.0	4	5
HV10-5R5G4	15	10	5.5	7.5